

**AMENDMENTS TO THE CLAIMS**

This Listing of the Claims will replace all prior versions, and listings, of claims in this application.

**Listing of the Claims:**

1. (Currently Amended) A communications device for detecting user transmitted symbols encoded in spread spectrum waveforms (hereinafter "user waveforms") comprising  
  
a first memory,  
  
a set of one or more first processing elements, coupled to the first memory, the set of first processing elements generating a matrix (hereinafter "R-matrix") representative of cross correlations among user waveforms and storing ~~the that~~ the R-matrix to contiguous locations within the first memory,  
  
a second processing element coupled with the first memory,  
  
the second processing element accessing the R-matrix from said contiguous locations within the first memory and generating symbol estimates as a composition of the R-matrix.
2. (Canceled)
3. (Original) The device of claim 1, comprising  
  
a second memory coupled with the set of first processing elements and a third processing element,  
  
the third processing element generating a matrix (hereinafter "gamma-matrix") representative of a correlation between a code associated with one user and those associated with one or more other users,  
  
the third processing element places the gamma-matrix in the second memory.

4. (Currently Amended) The device of claim 3, comprising  
  
the third processing element generating the gamma-matrix and placing that matrix in contiguous locations ~~location~~ within the second memory,  
  
the set of first processing elements accessing the gamma-matrix from contiguous locations within the second memory and generating the R-matrix.
5. (Currently Amended) The device of claim 3, comprising  
  
a multi-port switch coupled to the third processing element and to the second memory,  
  
wherein the third processing element places the gamma-matrix in the second memory via the multi-port data-switch.
6. (Original) The device of claim 3, wherein the gamma-matrix is a composition of a complex conjugate of the code associated with one user and a complex conjugate of the codes associated with one or more other users.
7. (Original) The device of claim 3, wherein the third processing element updates the gamma-matrix as users are added or removed from the spread spectrum system.
8. (Original) The device of claim 3, wherein the set of first processing elements generate the R-matrix as a composition of the gamma-matrix.
9. (Currently Amended) A communications device for detecting user transmitted symbols encoded in spread spectrum waveforms (hereinafter "user waveforms") comprising a first memory,  
  
a set of one or more first processing elements coupled to the first memory, the set of first processing elements generating a matrix (hereinafter "R-matrix") representative of cross correlations among user waveforms and storing the R-matrix to contiguous locations within the first memory,

a second processing element coupled with the first memory,

the second processing element accessing the R-matrix from contiguous locations within the first memory and generating symbol estimates as a composition of the R-matrix,

~~The device of claim 1, comprising~~

a host controller coupled to each of the set of first processing elements, wherein the host controller generates a partitioning of the R-matrix, that partitioning divides the R-matrix into one or more portions based on a number of users and a number of available processing elements,

the host controller assigns to each first processing element a portion of the R-matrix to generate according to the partitioning,

each of the first processing elements generating the assigned portion of the R-matrix according to the partitioning,

the host controller re-calculates the partitioning of the R-matrix when a user is added or removed from the spread spectrum system, and assigns a new portion of the R-matrix to each first processing element according to that new partitioning.

10. (Original) The device of claim 9, wherein each first processing element places its respective portion of the R-matrix in the first memory according to its respective partition such that each portion of the R-matrix is contiguous with respect to the other portions.
11. (Currently Amended) A communications device for detecting user transmitted symbols encoded in spread spectrum waveforms (hereinafter "user waveforms") comprising  
  
a first memory,  
  
a set of one or more first processing elements, coupled to a direct memory access engine (hereinafter "DMA engine"), the set of first processing elements generating a matrix

(hereinafter "R-matrix") representative of cross correlations among user waveforms, the DMA engine coupled with the first memory,

the DMA engine storing ~~the~~ that R-matrix to contiguous locations within the first memory,

a second processing element coupled with the first memory,

the second processing element accessing the R-matrix from contiguous locations within the first memory and generating symbol estimates as a composition of the R-matrix.

12. (Canceled).

13. (Original) The device of claim 11 comprising

a second memory coupled with the set of first processing elements and a third processing element,

the third processing element generating a matrix (hereinafter "gamma-matrix") representative of a correlation between a code associated with one user and those associated with one or more other users,

the third processing element places the gamma-matrix in the second memory.

14. (Currently Amended) The device of claim 13, wherein 11, comprising

the third processing element generates ~~generating~~ the gamma-matrix and places ~~placing~~ that matrix in contiguous locations ~~location~~ within the second memory, and

the set of first processing elements accesses ~~accessing~~ the gamma-matrix from contiguous locations within the second memory and generates ~~generating~~ the R-matrix.

15. (Currently Amended) The device of claim 13, comprising

a multi-port switch coupled to the third processing element and to the second memory,

wherein the third processing element places the gamma-matrix in the second memory via the data switch.

16. (Original) The device of claim 13, wherein the gamma-matrix is a composition of a complex conjugate of the code associated with one user and a complex conjugate of the codes associated with one or more other users.
17. (Original) The device of claim 13, wherein the third processing element updates the gamma-matrix as users are added or removed from the spread spectrum system.
18. (Original) The device of claim 13, wherein the set of first processing elements generate the R-matrix as a composition of the gamma-matrix.
19. (Original) The device of claim 11, comprising  
  
a host controller coupled to each of the set of first processing elements, the host controller generating a partitioning of the R-matrix, that partitioning divides the R-matrix into one or more portions based on a number of users and a number of available processing elements,  
  
the host controller assigns to each first processing element a portion of the R-matrix to generate according to the partitioning,  
  
each first processing element generating the assigned portion of the R-matrix according to the partitioning,  
  
the host re-calculating the partitioning of the R-matrix when a user is added or removed from the spread spectrum system, and assigning a new portion of the R-matrix to each first processing element according to that new partitioning.
20. (Original) The device of claim 19, wherein DMA engine places each portion of the R-matrix in the first memory according to the partitioning such that the each portion of the R-matrix is contiguous with respect to the adjacent portions.

21. (Currently Amended) A communications device for detecting user transmitted symbols encoded in spread spectrum waveforms (hereinafter "user waveforms") comprising
- a first memory,
- a set of one or more first processing elements, coupled to the first memory, the set of first processing elements generating a matrix (hereinafter "R-matrix") representative of cross correlations among user waveforms and storing that R-matrix to contiguous locations within the first memory,
- a second processing element coupled to the first memory, the second processing element accessing R-matrix from said contiguous locations ~~location~~ within the first memory and generating symbol estimates as a composition of the R-matrix,
- a second memory coupled with the set of first processing elements and a third processing element,
- the third processing element generating a matrix (hereinafter "gamma-matrix") representative of a correlation between a code associated with one user and those associated with one or more other users,
- wherein the third processing element places the gamma-matrix in the second memory.
22. (Canceled).
23. (Currently Amended) The device of claim 21, ~~wherein 22, comprising~~
- the third processing element places ~~generating the gamma-matrix and placing that the~~ gamma-matrix in contiguous locations ~~location~~ within the second memory,
- the set of first processing elements accessing the gamma-matrix from contiguous locations within the second memory and generating the R-matrix.
24. (Currently Amended) The device of claim 21~~22~~, comprising

a multi-port switch coupled to the third processing element and to the second memory,  
the third processing element places the gamma-matrix in the second memory via the data switch.

25. (Currently Amended) The device of claim 2122, wherein the gamma-matrix is a composition of a complex conjugate of the code associated with one user and a complex conjugate of the codes associated with one or more other users.
26. (Currently Amended) The device of claim 2122, wherein the third processing element updates the gamma-matrix as users are added or removed from the spread spectrum system.
27. (Currently Amended) The device of claim 2122, wherein the set of first processing elements generate the R-matrix as a composition of the gamma-matrix.
28. (Original) The device of claim 21, comprising  
  
a direct memory access engine (hereinafter "DMA engine") coupled with the set of second processing elements and the first memory,  
  
the DMA engine placing the R-matrix in contiguous locations within the first memory.
29. (Original) The device of claim 21, comprising  
  
a direct memory access engine (hereinafter "DMA engine") coupled with the third processing element and the second memory,  
  
the DMA engine placing the gamma-matrix in contiguous locations within the second-memory.